

ASYMPTOTIC CONTROL THEORY FOR A CLOSED STRING

ALEKSEY FEDOROV AND ALEXANDER OVSEEVICH

ABSTRACT. We develop an asymptotical control theory for one of the simplest distributed oscillating system — the closed string under a bounded load applied to a single distinguished point. We find exact classes of the string states that allows complete damping, and asymptotically exact value of the required time. By using approximate reachable sets instead of exact ones we design a dry-friction like feedback control, which turns to be asymptotically optimal. We prove the existence of the motion under the control by means of a rather explicit solution of a nonlinear wave equation. Remarkably, the solution is determined via purely algebraic operations. The main result is a proof of the asymptotic optimality of the designed control.

KEYWORDS maximum principle, reachable sets, linear system

MSC 2010: 93B03, 93B07, 93B52.

1. INTRODUCTION

It is well-known that the limit capabilities of a control system can be described in terms of reachable sets, i.e. sets of states reachable from a given state at a given time. In minimum-time problems it is convenient to pass to the backward time. By passing to the backward time, we can consider sets reachable from the terminal manifold. Geometrically, the minimum time control is organized as follows. Any state corresponds to a reachable set such that its boundary passes through this state. The minimum-time control at the current state forces our system move in the direction normal to the boundary of the corresponding reachable set.

Unfortunately, the reachable sets are difficult to study. However, sometime we possess an approximation of the reachable sets. In particular, for linear systems there is a systematic asymptotic theory of the reachable sets as time goes to infinity [1]. By substituting the approximate reachable set for the exact reachable set we can design a control. Alongside the simplicity this control might be asymptotically optimal. This type of control can be interpreted as an action of a generalized dry friction. The behavior of any system of finite number of linear oscillators under the dry-friction control has been studied in Refs [2, 3].

1.1. Problem statement. In this paper we apply this technique to control of a simple distributed system, the closed string under an impulsive force applied at a fixed point in the string. The phase space S of the system consists of pairs $\mathbf{f} = (f_0, f_1)$ of distributions on a one-dimensional torus $\mathcal{T}$, and the motion is governed by the string equation

$$(1) \quad \frac{\partial^2 f}{\partial t^2} = \frac{\partial^2 f}{\partial x^2} + u\delta, \quad |u| \leq 1.$$

Here $x \in [0, 2\pi]$ is the angle coordinate on the torus, t is time, $f_0 = f$, $f_1 = \frac{\partial f}{\partial t}$, δ is the Dirac δ -function. In other words, S is the space of initial data for Eq. (1). It is clear, that any solution of Eq. (1) with zero initial data is even. This is why we assume that S consists of pairs $\mathbf{f} = (f_0, f_1)$ of even distributions. The equation describes oscillations of the closed homogeneous string under a bounded

load applied to a fixed point (zero). We note that a mechanical model of such system can be not only a string, but also, e.g., a toroidal acoustic resonator.

Our goal is to design an easily implementable feedback control for damping the oscillations. This means that we do not necessarily want to stop the motion of the string as a whole, so that that our target manifold $\mathcal{C}$ consists of pairs of constants

$$(2) \quad \mathcal{C} = \{(c_0, c_1)^* \in \mathbb{R}^2 \subset S\}.$$

Another useful point of view is to take the factor-space $\bar{S} = S/\mathcal{C}$ as the phase space of our system, and try to reach zero in this space. This is reasonable, because the target space $\mathcal{C}$ is invariant under the natural flow, associated with the string equation. In what follows, we deal with a class of problems of minimum-time steering from the initial state to a terminal manifold $\mathcal{C}$ consisting of a pair of constants (2). More specifically, we study three problems:

- (1) Complete stop at a given point: $\mathcal{C} = 0$
- (2) Stop moving: $\mathcal{C} = \mathbb{R} \times 0$
- (3) Oscillation damping: $\mathcal{C} = \mathbb{R}^2$

The main result of the present paper is the design of the generalized dry-friction control and the proof of its asymptotic optimality in the stop moving problem. A summary of our results was presented in Ref. [4].

1.2. Structure. The paper is organized as follows. In Section 2 we discuss a mechanical model of the considered system. In Section 3 we find an explicit form of the support functions of the reachable sets. We then study the asymptotic behavior of the reachable sets as time goes to infinity using the language of shapes in Section 4. In Section 5 on the basis of this study we design the generalized dry-friction control for our system. In particular, we invoke the notion of the duality transform for a smooth description of the generalized dry-friction. In Section 7 we show that in the stop-moving problem the motion of the system under the dry-friction control can be described via solution of a nonlinear wave equation of second order. We then restate the nonlinear wave equation as a nonlinear first order equation. In Section 9 we prove the existence of the motion under the generalized dry-friction by means of a rather explicit solution of the nonlinear equation. Remarkably, it is made via purely algebraic operations. In Section 9 we demonstrate that the suggested control is asymptotically optimal, and describe features of this control in Section 10. Finally, we conclude in Section 11. Appendices II and IV contain a number of auxiliary results.

2. STRING AS A MECHANICAL SYSTEM.

The equations of motion of the free string (1) are that of the following Lagrangian system, where q is an even function such that $\frac{\partial q}{\partial x} \in L_2(\mathcal{T})$, and the Lagrangian

$$(3) \quad L(q, \dot{q}) = \frac{1}{2} \int_{\mathcal{T}} |\dot{q}|^2(x) dx - \frac{1}{2} \int_{\mathcal{T}} \left| \frac{\partial q}{\partial x} \right|^2(x) dx - uq(0),$$

so that $\frac{1}{2} \int_{\mathcal{T}} |\dot{q}|^2 dx$ is the kinetic energy, and $\frac{1}{2} \int_{\mathcal{T}} \left| \frac{\partial q}{\partial x} \right|^2 dx$ is the potential energy of the system. The Lagrangian corresponds to the Hooke's law: the strain (deformation) is proportional to the applied stress. In terms of the Lagrangian the stress at point x is $\frac{\delta L}{\delta q}(x) = \frac{\partial q}{\partial x}(x)$, and the strain at x is $\frac{\partial q}{\partial x}(x)$, so that the coefficient of proportionality is 1.

The string also allows for a Hamiltonian description. The phase space is then the set of pairs (p, q) , where p is an (even) function from $L_2(\mathcal{T})$, q is an (even) function

from the space N of functions such that $\frac{\partial q}{\partial x} \in L_2(\mathcal{T})$, and the Hamiltonian

$$(4) \quad H(p, q) = \frac{1}{2} \int_{\mathcal{T}} |p|^2(x) dx + \frac{1}{2} \int_{\mathcal{T}} \left| \frac{\partial q}{\partial x} \right|^2(x) dx + uq(0).$$

The canonical symplectic structure $\omega = dp \wedge dq$ is given by $\omega((X, X'), (Y, Y')) = \langle X, Y' \rangle - \langle X', Y \rangle$. Here $X, Y \in L_2(\mathcal{T})$, $X', Y' \in N$, and the angle brackets stand for the scalar product in $L_2(\mathcal{T})$.

Finally, the Pontryagin Hamiltonian H^{pont} in “coordinates” $\mathbf{f} = (f_0, f_1)$ takes the form

$$(5) \quad H^{\text{pont}}(\mathbf{f}, \mathbf{r}) = \langle f_1, \xi_0 \rangle + \langle \Delta f_0, \xi_1 \rangle + |\xi_1(0)|,$$

with $\mathbf{r} = (\xi_0, \xi_1)$ being the adjoint variables.

3. THE SUPPORT FUNCTION OF REACHABLE SETS

The first issue we deal with is that of controllability of the considered system. We approach it by computation of the support function. The approach has much in common with that of Ref. [5].

To make a comparison with the finite-dimensional case clear, we rewrite the governing equation in the form of first-order system

$$(6) \quad \begin{aligned} \frac{\partial \mathbf{f}}{\partial t} &= A\mathbf{f} + Bu, \quad |u| \leq 1, \\ A &= \begin{pmatrix} 0 & 1 \\ \Delta & 0 \end{pmatrix}, \quad \Delta = \frac{\partial^2}{\partial x^2}, \quad B = \begin{pmatrix} 0 \\ \delta \end{pmatrix}. \end{aligned}$$

We commence with computing the support function $H = H_{D(T)}(\xi)$ of the reachable set $D(T)$, $T \geq 0$ of system (6) with zero initial condition. In other words, we have to find $H = \sup_u \langle \mathbf{f}(T), \xi \rangle$, where $\xi \in S^*$ is a dual vector, and the sup is taken over admissible controls. Towards this end, we extend $\xi = (\xi_0, \xi_1)$ to the solution of the Cauchy problem

$$(7) \quad \frac{\partial \xi}{\partial t} = -A^* \xi, \quad \xi(T) = \xi, \quad A^* = \begin{pmatrix} 0 & \Delta \\ 1 & 0 \end{pmatrix}$$

where A^* is the adjoint operator to A . These equations are exactly the equations for the adjoint variables of the Pontryagin maximum principle. We then have

$$(8) \quad \frac{d}{dt} \langle \mathbf{f}(t), \xi(t) \rangle = \langle A\mathbf{f} + Bu, \xi \rangle - \langle \mathbf{f}, A^* \xi \rangle = \langle Bu, \xi \rangle = u(t) \xi_1(0, t).$$

A standard formal computation shows that

$$(9) \quad H = H_{D(T)}(\xi) = \sup_{|u| \leq 1} \int_0^T u(t) \xi_1(0, t) dt = \int_0^T |\xi_1(0, t)| dt.$$

The reachable sets $D(T)$, $T \geq 0$ are closed in the standard topology of distributions, and of course they are convex. Therefore they are uniquely defined by their support functions.

Now we can characterize the vectors $\mathbf{f}$ reachable from zero in time T as follows:

$$(10) \quad \mathbf{f} \in D(T) \Leftrightarrow \langle \mathbf{f}, \xi \rangle \leq \int_0^T |\xi_1(0, t)| dt \quad \text{for any } \xi \in S^*.$$

Here the function $x, t \mapsto \xi_1(x, t)$ is defined via solution of the Cauchy problem (7).

In particular, the space $\mathcal{D}$ generated by vectors $\mathbf{f} \in \bigcup_{T \geq 0} D(T)$ reachable from zero in an arbitrary time $T \geq 0$ is the dual space to the Frechet space of vectors ξ with finite norms

$$(11) \quad \|\xi\| = \|\xi\|_T = \int_0^T |\xi_1(0, t)| dt$$

for any $T > 0$. This space $\mathcal{D}$ coincides with the set of vectors reachable from zero in an arbitrary time $T \geq 0$ by means of a bounded (not necessarily by 1) control.

It is not difficult to compute $\xi_1(0, t)$ in terms of the Fourier coefficients of the functions $\psi = \xi_1$ and $\phi = \xi_0$. Suppose that

$$(12) \quad \psi(x, t) = \sum_{n=-\infty}^{\infty} \psi_n(t) e^{inx}$$

is the Fourier expansion of ξ_1 . Since ψ is an even and real distribution, the coefficients ψ_n are real, and $\psi_n = \psi_{-n}$, so that Eq. (12) is, in fact, the cosine-expansion:

$$(13) \quad \psi(x, t) = \sum_{n=0}^{\infty} \psi_n(t) \cos nx.$$

The quantity we want to compute is

$$(14) \quad \|\xi\| = \int_0^T |\xi_1(0, t)| dt = \int_0^T \left| \sum \psi_n(t) \right| dt.$$

From Eq. (7) we immediately conclude that for $n \neq 0$

$$(15) \quad \psi_n(t) = e^{int} a_n + e^{-int} b_n,$$

where a_n, b_n are constants. For $n = 0$ we have $\psi_0(t) = a_0 + b_0 t$. It is clear that for $n \neq 0$

$$(16) \quad a_n = \frac{1}{2} \left(\psi_n + \frac{\phi_n}{in} \right), \quad b_n = \frac{1}{2} \left(\psi_n - \frac{\phi_n}{in} \right),$$

where ϕ_n is the n th Fourier coefficient of ϕ , and

$$(17) \quad a_0 = \psi_0, \quad b_0 = \phi_0.$$

The Fourier coefficients of ϕ , like that of ψ , are real, and even with respect to n .

3.1. Natural norm in the dual space. By an easy computation we conclude that

$$(18) \quad \|\xi\| = \|\xi\|_T = \int_0^T \left| \sum_{n \neq 0} \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) + \psi_0 + \phi_0 t \right| dt.$$

Suppose that $T \geq 2\pi$. Then, the Banach norm $\|\xi\|$ is equivalent to the following more familiar Sobolev-type norm

$$(19) \quad \|\xi\|' = \|\xi_1\|_1 + \|\eta\|_1.$$

Here $\|g\|_1 = \int_{-T/2}^{T/2} |g| dt$ is the usual L_1 -norm, and $\eta(t) = \int_0^t \xi_0(x) dx$. Indeed, denote by f the integrand

$$(20) \quad f(t) = \sum_{n \neq 0} \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) + \psi_0 + \phi_0 t.$$

The norm $\|\xi\|$ is equivalent to $\|f\|_1 = \int_{-T/2}^{T/2} |f| dt = \int_{-T/2}^{T/2} |f^+ + f^-| dt$, where

$$(21) \quad \begin{aligned} f^+(t) &= \sum_{n \neq 0} \psi_n \cos nt + \psi_0 = \xi_1(t), \\ f^-(t) &= \sum_{n \neq 0} \frac{\phi_n}{n} \sin nt + \phi_0 t = \eta(t), \end{aligned}$$

are even and odd parts of the function f , respectively.

Indeed, put $g(t) = f(t) - \phi_0 t$. Then, $\|\xi\|$ is equivalent to $\int_0^T |g| dt + |\phi_0|$, while $\|f\|_1$ is equivalent to $\int_{-T/2}^{T/2} |g| dt + |\phi_0|$. Since the function g is 2π -periodic, and

intervals of integration have length $T \geq 2\pi$, both integrals $\int_0^T |g|dt$, and $\int_{-T/2}^{T/2} |g|dt$ are equivalent to $\int_0^{2\pi} |g|dt$.

The L_1 -norms of functions $f^\pm$ can be estimated via the L_1 -norm of f :

$$(22) \quad \|f^\pm\|_1 \leq \|f\|_1.$$

Therefore, $\|\xi\|' = \|f^+\|_1 + \|f^-\|_1 \leq 2\|f\|_1$. On the other hand, it is obvious that

$$(23) \quad \|f\|_1 \leq \|f^+\|_1 + \|f^-\|_1 = \|\xi_1\|_1 + \|\eta\|_1 = \|\xi\|'.$$

We conclude that the norms $\|\xi\|'$ and $\|\xi\|$ are equivalent indeed. Therefore, if $T \geq 2\pi$ the dual space to the Banach space with norm $\|\xi\|$ coincides with the space of pairs $\mathbf{f} = (f_0, f_1)$, where $\frac{\partial f_0}{\partial x} \in L_\infty$, and $f_1 \in L_\infty$. Thus, it is possible to damp the string, where the initial state $\mathbf{f} = (f_0, f_1)$ possesses these properties, by a bounded load applied to a fixed point. Here by damping we mean the complete stop, when not just oscillations, but also the displacement of the string as a whole is forbidden.

Remark. Our arguments show that the equivalence class of the norm $\|\xi\|_T$ does not depend on T provided that $T \geq 2\pi$. Theorem 1 and Theorem 2 give a more quantitative statement of this independence of T .

3.2. Damping the oscillations. In order to deal with damping oscillations only, it suffices to make an analog of previous computations in the factor-space $S/\mathcal{C}$. The corresponding support functions are almost the same as those previously found. We just have to assume that the zero-mode coefficients ϕ_0, ψ_0 of the dual vectors ξ are zero. Then, the formula for support functions of the corresponding reachable sets $\overline{D}(T)$ takes the following form:

$$(24) \quad H_{\overline{D}(T)}(\xi) = \int_0^T \left| \sum \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) \right| dt = \int_0^T \left| \xi_1(y) + \int_0^y \xi_0(x) dx \right| dy.$$

Basically the same, but simpler arguments than that of previous subsection 3.1, prove that states $\mathbf{f} = (f_0, f_1)$, where $\frac{\partial f_0}{\partial x} \in L_\infty$, and $f_1 \in L_\infty$ are exactly those that can be damped.

4. THE SHAPE OF THE REACHABLE SET $D(T)$

Following Ref. [1], one can easily find an asymptotic formula for the above support function (18). For $T > 0$ define a linear isomorphism $C(T) : S \rightarrow S$ by $C(T)\mathbf{f} = \frac{1}{T}(f_0, f_1^T)^*$, where

$$(25) \quad g^T(t) = \sum_{n \neq 0} g_n \cos nt + \frac{1}{T}g_0, \text{ if } g(t) = \sum_{n \neq 0} g_n \cos nt + g_0.$$

It is clear that

$$(26) \quad H_{C(T)D(T)}(\xi) = \frac{1}{T} \int_0^T \left| \sum_{n \neq 0} \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) + \psi_0 + \frac{\phi_0}{T}t \right| dt,$$

where ξ is the pair (ξ_0, ξ_1) , and $\xi_0(x) = \sum \phi_n \cos nx$, $\xi_1(x) = \sum \psi_n \cos nx$.

We then have the following precise statement.

Theorem 1. *Consider problem (1) from the Introduction, corresponding to the terminal manifold $\mathcal{C} = 0$. Then as $T \rightarrow \infty$ we have the following limit formula:*

$$(27) \quad \begin{aligned} & \lim_{T \rightarrow \infty} H_{C(T)D(T)}(\xi) \\ &= \frac{1}{2\pi} \int_0^{2\pi} \int_0^1 \left| \sum_{n \neq 0} \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) + \psi_0 + \phi_0 \tau \right| dt d\tau. \end{aligned}$$

Proof. The easy proof follows arguments from the basic results of Ref. [1], which we reproduce here for the reader's convenience. It suffices to consider T of the form $T = 2\pi N$, $N \in \mathbb{Z}$. Then, we can rewrite Eq. (26) in the following form:

$$(28) \quad H_{C(T)D(T)}(\xi) = \frac{1}{2\pi N} \sum_{i=0}^{N-1} \int_0^{2\pi} \left| g(t) + \phi_0 \left(\frac{i}{k} + \frac{t}{2\pi N} \right) \right| dt,$$

where

$$(29) \quad g(t) = \sum_{n \neq 0} \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) + \psi_0$$

is a 2π -periodic function. We then note that the right-hand side of Eq. (28) equals

$$(30) \quad \frac{1}{2\pi N} \sum_{i=0}^{N-1} \int_0^{2\pi} \left| g(t) + \phi_0 \frac{i}{k} \right| dt + O\left(\frac{1}{N}\right),$$

which is the Riemann sum for the integral over $[0, 1]$ of the continuous function

$$(31) \quad \tau \mapsto \frac{1}{2\pi} \int_0^{2\pi} |g(t) + \phi_0 \tau| dt.$$

Since the Riemann sums converge to the integral

$$(32) \quad \frac{1}{2\pi} \int_0^1 \int_0^{2\pi} |g(t) + \phi_0 \tau| dt d\tau \text{ as } N \rightarrow \infty,$$

the statement is proved. $\square$

We remind that the shape $\text{Sh } \Omega$ of a set $\Omega \subset S$ is the orbit of the group of linear (topological) isomorphisms of the space S acting on Ω . In terms of shapes one can say that the limit shape

$$(33) \quad \text{Sh}_\infty = \lim_{T \rightarrow \infty} \text{Sh } D(T)$$

is related to the convex body Ω corresponding to the support function

$$(34) \quad H_\Omega(\xi) = \frac{1}{2\pi} \int_0^{2\pi} \int_0^1 \left| \sum_{n \neq 0} \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) + \psi_0 + \phi_0 \tau \right| dt d\tau.$$

This means that the shape of the convex set with the support function (34) coincides with Sh_∞ . Similarly, in the reduced space $\overline{S}$ we have the following precise result.

Theorem 2. *Consider problems (2)-(3) from the Introduction, corresponding to the terminal manifolds $\mathcal{C} = \mathbb{R} \times 0$, or $\mathcal{C} = \mathbb{R}^2$. Then, the following limit formula holds:*

$$(35) \quad \lim_{T \rightarrow \infty} \frac{1}{T} H_{\overline{D}(T)}(\xi) = \frac{1}{2\pi} \int_0^{2\pi} \left| \sum \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) \right| dt = \frac{1}{2\pi} \int_0^{2\pi} |\zeta(t)| dt.$$

where $\zeta(t) = \xi_1(t) + \int_0^t \xi_0(x) dx$.

Note that the operator of multiplication by $(T)^{-1}$ in the factor-space $\overline{S}$ is induced by the operator $C(T)$, and Eq. (35) describes the limit shape $\lim_{T \rightarrow \infty} \text{Sh } \overline{D}(T)$. Denote by Ω the convex body such that its support function is given by the right-hand side of (35):

$$(36) \quad H_\Omega(\xi) = \frac{1}{2\pi} \int_0^{2\pi} \left| \sum \left(\psi_n \cos nt + \frac{\phi_n}{n} \sin nt \right) \right| dt = \frac{1}{2\pi} \int_0^{2\pi} |\zeta(t)| dt.$$

According to Theorem 2 the set $T\Omega$ is an approximation of $D(T)$ if T is large.

5. DRY-FRICTION CONTROL

Our control design is based on the following idea: The optimal control at state $\mathbf{f}$ implements the steepest descent in the direction normal to boundaries of the reachable sets $D(T)$. Our control implements the steepest descent in the direction normal to boundaries of the approximate reachable sets $T\Omega$, where Ω is defined via Eq. (36). This means that in notations of Eq. (35) we have

$$(37) \quad u(\mathbf{f}) = -\text{sign}\langle B, \xi \rangle = -\text{sign} \xi_1(0) = -\text{sign} \zeta(0),$$

where the momentum ξ is to be found via the equation

$$(38) \quad T^{-1}\mathbf{f} = \frac{\partial H_\Omega}{\partial \xi}(\xi),$$

or, equivalently, $\mathbf{f} = (f_0, f_1)$, where

$$(39) \quad T^{-1}f_0(x) = -\int_0^x (\text{sign} \zeta(y))^- dy, \quad T^{-1}f_1(x) = (\text{sign} \zeta(x))^+,$$

where the notation $f^\pm$ stands for even/odd part of the function f :

$$(40) \quad f^\pm(x) = \frac{1}{2}(f(x) \pm f(-x)).$$

These identities are to be understood as inclusions, because the sign-map is multivalued. Namely, their precise meaning is

$$(41) \quad T^{-1}f_0(x) = -\int_0^x \phi(y)^- dy, \quad T^{-1}f_1(x) = \psi(x)^+,$$

where $\phi(y) \in \text{sign} \zeta(y)$, and $\psi(x) \in \text{sign} \zeta(x)$.

5.1. Duality transform. We invoke a general duality transformation related to Eq. (38). Toward this end, we denote the function H_Ω just by $H = H(\xi)$, and the factor T by $\rho(\mathbf{f})$. Then the relation between H and ρ is similar to the Legendre transformation:

$$(42) \quad \langle \mathbf{f}, \xi \rangle = \rho(\mathbf{f})H(\xi), \quad \rho(\mathbf{f}) = \max_{H(\xi) \leq 1} \langle \mathbf{f}, \xi \rangle, \quad H(\xi) = \max_{\rho(\mathbf{f}) \leq 1} \langle \mathbf{f}, \xi \rangle,$$

where the correspondence $\mathbf{f} \rightleftharpoons \xi$ has the following form:

$$(43) \quad \mathbf{f} = \rho(\mathbf{f}) \frac{\partial H}{\partial \xi}(\xi),$$

$$(44) \quad \xi = H(\xi) \frac{\partial \rho}{\partial \mathbf{f}}(\mathbf{f}).$$

Here ξ and $\mathbf{f}$ are the points where the maximums in (42) are attained. These relations make sense provided that H and ρ are norms, i.e. homogeneous of degree 1 convex functions such that the sublevel sets $\{H(\xi) \leq 1\}$ and $\{\rho(\mathbf{f}) \leq 1\}$ are convex bodies. These sublevels are mutually polar to each other. In other words, if $\Omega = \{\rho(\mathbf{f}) \leq 1\}$, and $\Omega^\circ = \{H(\xi) \leq 1\}$, then $\Omega = \{\mathbf{f} : \langle \mathbf{f}, \xi \rangle \leq 1, \xi \in \Omega^\circ\}$ and vice versa. In the language of Banach spaces, the normed spaces $(\mathbb{V}, \rho)$ and $(\mathbb{V}^*, H)$ are dual to each other. The derivatives in Eq. (44) should be understood as subgradients. If the functions H and ρ are differentiable then Eq. (44) has the classical meaning. If one of the functions H and ρ is differentiable and strictly convex, then, the other one is also so.

The above discussion of duality is absolutely correct in the finite dimensional setting, but is not literally correct in infinite dimension, because there is no good duality theory for general Banach spaces: double dual to a Banach space is not necessarily isomorphic to the initial one. Still it is a very useful starting point for intuition.

In the cases at hand we need to calculate the dual function ρ for the function $H = H_\Omega$ from Eq. (36). We then arrive at the following result.

Theorem 3. *Consider problems (2) – (3) from the Introduction, corresponding to the terminal manifolds $\mathcal{C} = \mathbb{R} \times 0$, or $\mathcal{C} = \mathbb{R}^2$.*

- (1) *If $\mathcal{C} = \mathbb{R}^2$, then $\rho(\mathbf{f}) = 2\pi \left| \frac{\partial f_0}{\partial x} + f_1 \right|_\infty$, where the norm $|\phi|_\infty$ of a function ϕ on the torus $\mathcal{T} = \mathbb{R}/2\pi\mathbb{Z}$ is $\inf_c \sup_{x \in \mathcal{T}} |\phi(x) + c|$, where $c \in \mathbb{R}$ is an arbitrary constant.*
- (2) *If $\mathcal{C} = \mathbb{R} \times 0$, then $\rho(\mathbf{f}) = 2\pi \left| \frac{\partial f_0}{\partial x} + f_1 \right|_\infty$, where the norm $|\phi|_\infty$ is the sup-norm of the function ϕ on the torus $\mathcal{T} = \mathbb{R}/2\pi\mathbb{Z}$.*

Proof. We consider only the problem (2) of Theorem 3, because the problem (3) is quite similar. We note that in case (1)

$$(45) \quad |\phi|_\infty = \frac{1}{2} (\sup \phi - \inf \phi).$$

We note that $\frac{\partial f_0}{\partial x}$ is an odd function, while f_1 is even. This implies that the norm $\rho(\mathbf{f})$ is equivalent to (although does not coincide with) $\max \left(\left| \frac{\partial f_0}{\partial x} \right|_\infty, |f_1|_\infty \right)$.

To prove the theorem we define $\rho_0(\mathbf{f})$ by the formula

$$(46) \quad \rho_0(\mathbf{f}) = \left| \frac{\partial f_0}{\partial x} + f_1 \right|_\infty,$$

and check that $H(\xi) = \frac{1}{2\pi} \max_{\rho_0(\mathbf{f}) \leq 1} \langle \mathbf{f}, \xi \rangle$. Toward this end, put

$$(47) \quad \psi_0(t) = \int_0^t \xi_0(x) dx, \quad \psi_1(t) = \xi_1(t), \quad \psi = \psi_0 + \psi_1,$$

and

$$(48) \quad \phi_0 = \frac{\partial f_0}{\partial x}, \quad \phi_1 = f_1, \quad \phi = \phi_0 + \phi_1.$$

Denote by $\int_{\mathcal{T}} f$, where $\mathcal{T} = \mathbb{R}/2\pi\mathbb{Z}$, the normalized integral $\frac{1}{2\pi} \int_0^{2\pi} f(t) dt$. Remind that $\langle \mathbf{f}, \xi \rangle$ stands for $\int_0^{2\pi} \langle \mathbf{f}(t), \xi(t) \rangle dt$.

Then,

$$(49) \quad \int_{\mathcal{T}} \phi \psi = \int_{\mathcal{T}} \phi_0 \psi_0 + \int_{\mathcal{T}} \phi_1 \psi_1 = \frac{1}{2\pi} \langle \mathbf{f}, \xi \rangle,$$

because the integrals $\int_{\mathcal{T}} \phi_0 \psi_1 dt$, $\int_{\mathcal{T}} \phi_1 \psi_0 dt$ vanish, being integrals of odd functions over $\mathcal{T} = \mathbb{R}/2\pi\mathbb{Z}$. It is clear from Eq. (49), that the maximum of $\int_{\mathcal{T}} \phi \psi dt$, taken over ϕ such that $|\phi|_\infty \leq 1$, coincides with the maximum of $\langle \mathbf{f}, \xi \rangle$, taken over $\mathbf{f}$ such that $\rho_0(\mathbf{f}) \leq 1$. However, it is trivial that the maximum of $\int_{\mathcal{T}} \phi \psi = \int_{\mathcal{T}} |\psi|$. The latter value, according to Eq. (36), equals $H(\xi)$. $\square$

One can regard our computation of the norm ρ as an a priori estimate for solutions of the wave equation.

Theorem 4. *Suppose $\mathbf{f} = (f_0, f_1)$, is a solution of the Cauchy problem*

$$(50) \quad \frac{\partial \mathbf{f}}{\partial t} = A\mathbf{f} + Bu, \quad |u| \leq 1, \quad \mathbf{f}(0) = 0,$$

where $B = (0, \delta)$, $u = u(t)$. If $T \geq 2\pi$ we then have

$$(51) \quad \rho(\mathbf{f}(T)) = 2\pi \left| \frac{\partial f_0}{\partial x} + f_1 \right|_\infty \leq T.$$

The following trivial corollary, where previous notations are retained, is quite important for us:

Corollary 1. *Suppose $\mathbf{f} = (f_0, f_1)$, is a solution of $\frac{\partial \mathbf{f}}{\partial t} = A\mathbf{f} + Bu$, $|u| \leq 1$, while $\tilde{\mathbf{f}}$ is control-free: $\frac{\partial \tilde{\mathbf{f}}}{\partial t} = A\tilde{\mathbf{f}}$, and $\tilde{\mathbf{f}}(0) = \mathbf{f}(0)$. Then provided that $T \geq 2\pi$ we have*

$$(52) \quad \left| (f_1 - \tilde{f}_1)(T) \right|_{\infty} \leq \frac{1}{2\pi} T.$$

6. COMPUTATION OF THE BASIC CONTROL

Consider Problem (2) from the Introduction, corresponding to the terminal manifolds $\mathcal{C} = \mathbb{R} \times 0$. In order to find the control we need to solve Eqs. (39) as explicitly as possible. In other words, we have to find function ζ such that

$$(53) \quad T^{-1} \frac{\partial f_0}{\partial x}(x) \in -\text{sign } \zeta(x), \quad T^{-1} f_1(x) \in \text{sign } \zeta(x).$$

Our discussion of duality, in particular Eq. (44) shows that the solution is given by

$$(54) \quad T = \rho(\mathbf{f}) = 2\pi \left| \frac{\partial f_0}{\partial x} + f_1 \right|_{\infty}, \quad \zeta = \frac{\partial \rho}{\partial \mathbf{f}_1}(\mathbf{f}).$$

The final expression for the control has the following form:

$$(55) \quad u(\mathbf{f}) = -\text{sign } \zeta(0) = -\text{sign } f_1(0),$$

where we take into account Eq. (39) and the vanishing at 0 of the odd part of the function $x \mapsto \text{sign } \zeta(x)$. Thus, we obtain indeed a generalization of the dry friction, for it acts with maximal possible amplitude against the velocity, because $f_1(0)$ is exactly the velocity of the point, where the load is applied. Control (55) leads to the nonlinear wave equation of the following form:

$$(56) \quad \frac{\partial^2 f}{\partial t^2} = \frac{\partial^2 f}{\partial x^2} - \text{sign} \left(\frac{\partial f}{\partial t}(0) \right) \delta$$

governing the damping process. There are no a standard existence and uniqueness theorem for the Cauchy problem for Eq. (56). The problem is to extend to infinite-dimensional case the classical results of Filippov [6] concerning existence, and the uniqueness theorem of Bogaevsky [7].

7. RESTATEMENT OF THE MODEL

Previous considerations stress the importance of the function

$$(57) \quad g = \frac{\partial f_0}{\partial x} + f_1.$$

Knowledge of this function is almost equivalent to the knowledge of both functions f_0 and f_1 . Indeed, the function $\partial f_0 / \partial x$ is odd and f_1 is even. Therefore, knowledge of these functions is equivalent to the knowledge of the function g . On the other hand the knowledge of $\partial f_0 / \partial x$ gives a complete information on f_0 up to an additive constant. This constant is irrelevant if the goal of our damping process is to stop oscillation, or to stop motion of the string at an unspecified point. The law of the controlled motion given by Eqs. (1), (55), and (56) can be restated as follows:

$$(58) \quad \left(\frac{\partial}{\partial t} - \frac{\partial}{\partial x} \right) g(x, t) = \delta(x) u(t), \quad |u| \leq 1.$$

This form of the governing law has its merits. In particular, it can be made rather explicit: One can rewrite Eq. (58) as follows:

$$(59) \quad \frac{d}{dt} g(x - t, t) = \delta(x - t) u(t),$$

which means that

$$(60) \quad g(x-t, t) = g(x, 0) + \int_0^t \delta(x-s)u(s)ds = g(x, 0) + \sum_I u(x+2k\pi),$$

where the summation is over the set $I = I_t$ of $k \in \mathbb{Z}$ such that $x+2k\pi \in [0, t]$. By the change of variables $z = x-t$ we arrive at:

$$(61) \quad g(z, t) = g(z+t, 0) + \sum_J u(z+t+2k\pi),$$

where the summation is over the set $J = J_t$ of $k \in \mathbb{Z}$ such that $z+2k\pi \in [-t, 0]$.

Eq. (61) should be understood as follows: Here g is a bounded measurable function of x, t and u is a bounded measurable function of t , the curve $t \mapsto g(\cdot, t)$ is continuous as a map from real line to distributions depending on the space variable x . Eq. (61) does not hold pointwise, but expresses an equality in the space of curves of distributions wrt x .

8. EXISTENCE OF THE MOTION UNDER DRY-FRICTION CONTROL

We have to obtain an existence theorem for initial value problem for the nonlinear wave equation (56). By using transformation (57) the task reduces to solution of the functional equation

$$(62) \quad g(z, t) = g(z+t, 0) - \sum_J \text{sign } g(0, z+t+2k\pi),$$

which in turn can be reduced to the search for the function $g(0, t)$, $t \geq 0$, because this defines the control law $u(t) = -\text{sign } g(0, t)$.

This is quite nontrivial, because the function $\phi(t) = g(0, t)$, we are looking for, should satisfy a functional equation. The first step in establishing the desired functional equation is to make Eq. (62) hold pointwise. It is explained in the previous section that this equation expresses an equality in the space of curves of distributions of x . In order to make Eq. (62) hold pointwise we consider the one-sided averaging operators

$$(63) \quad \text{Av}^{\pm\epsilon} : f(z, t) \mapsto \frac{1}{\epsilon} \int_0^{\pm\epsilon} f(z+x, t)dx, \quad \text{Av}^{\pm} : f \mapsto \lim_{\epsilon \rightarrow 0} \text{Av}^{\pm\epsilon}(f),$$

and more standard two-sided operator

$$(64) \quad \text{Av}^\epsilon : f(z, t) \mapsto \frac{1}{2\epsilon} \int_{-\epsilon}^{\epsilon} f(z+x, t)dx, \quad \text{Av} : f \mapsto \lim_{\epsilon \rightarrow 0} \text{Av}^\epsilon(f).$$

We note that, according to the Lebesgue differentiation theorem, the limit averaging operators $\text{Av}^{\pm}$ and Av are identities when applied to any L_1 -function. The reason for application of these operators is that, if operators $\text{Av}^{\pm\epsilon}$ are applied to the right-hand and the left-hand sides of Eq. (62), the obtained equation holds *pointwise*. In particular,

$$(65) \quad \begin{aligned} \text{Av}^\epsilon(g)(0, t) &= \text{Av}^\epsilon(g)(t, 0) - \\ &\sum \frac{1}{2\epsilon} \int_{-\epsilon}^{\epsilon} u(z+t+2k\pi) 1_{[-t, 0]}(z+t+2k\pi) dz = \\ &\text{Av}^\epsilon(g)(t, 0) - \frac{1}{2} \text{Av}^{-\epsilon}(u)(t) - \sum_{k \neq 0} \text{Av}^\epsilon(u)(t+2k\pi), \end{aligned}$$

where $u(t) = -\text{sign } g(0, t)$, summation is over the set of $k \in \mathbb{Z}$ such that $2k\pi \in [-t, 0]$, and $\epsilon < t$.

To state the desired functional equation consider the function $\phi(t) = \text{Av}(g)(0, t)$. It follows from Eq. (65) by passing to the limit $\epsilon \rightarrow 0$ that this function does exist in $L_\infty(0, \infty)$. It also follows from Eq. (65) that

$$(66) \quad \phi(t) = G(t) - \frac{1}{2} \text{sign } \phi(t) - \sum_{k \neq 0, 2k\pi \in [-t, 0]} \text{sign } \phi(t + 2k\pi),$$

where $G(t) = g(t, 0)$ is the given initial 2π -periodic function. Solution of this equation gives at the same time a rigorously defined solution to the nonlinear wave equation (56).

Thus, we have to solve the equation

$$(67) \quad \phi(t) + \frac{1}{2} \text{sign } \phi(t) + \sum_{k \neq 0, 2k\pi \in [-t, 0]} \text{sign } \phi(t + 2k\pi) = G(t),$$

where G is a given function, and ϕ is unknown. Note that the function ϕ need not be periodic. It should be defined for nonnegative t . Note also that if $t < 2\pi$, the latter equation reduces to a very simple one:

$$(68) \quad \phi(t) + \frac{1}{2} \text{sign } \phi(t) = G(t),$$

which, obviously, has a unique solution, since the map $x \mapsto x + \text{sign } x$ is a strictly monotone increasing (multivalued) function. More explicitly, the solution $\phi(t) = G(t) - \frac{1}{2}$ if $G(t) > \frac{1}{2}$, and $\phi(t) = G(t) + \frac{1}{2}$ if $G(t) < -\frac{1}{2}$. Otherwise, $\phi(t) = 0$. Note that $|\phi(t)| \leq |G(t)|$ in the considered interval $[0, 2\pi)$ of values of the argument t .

It is better rewrite the above equation (68) in the form

$$(69) \quad \phi(t) + \frac{1}{2} v(t) = G(t), \quad v(t) = \text{sign } \phi(t),$$

where sign-function is regarded as multivalued: $\text{sign}(0) = [-1, 1]$. Then, the a priori multivalued $\text{sign } \phi(t)$ is defined by (69) uniquely. If $t < 2\pi$ we obtain from Eq. (67) and periodicity $G(t + 2\pi) = G(t)$ that

$$(70) \quad \phi(t + 2\pi) + \frac{1}{2} \text{sign } \phi(t + 2\pi) = G(t) - \text{sign } \phi(t),$$

which allows to extend by the preceding arguments the function $\phi(t)$ from $t \in [0, 2\pi)$ to any positive value of t . By the already used arguments we obtain that $|\phi(t)| \leq |G(t)|$ for all $t \geq 0$. We then have the following precise statement.

Theorem 5. *The Cauchy problem for the nonlinear wave equation*

$$(71) \quad \left(\frac{\partial}{\partial t} - \frac{\partial}{\partial x} \right) g(x, t) = -\delta(x) \text{sign } g(0, t),$$

where $g(x, 0)$ is a given bounded (Borel-measurable) function possesses a unique bounded solution for $t \geq 0$. The functions $\phi(t) = g(0, t)$ and $u(t) = -\text{sign } g(0, t)$ form a unique solution of functional equation (67).

We call the flow $g = g(\cdot, 0) \mapsto \Phi_t(g) = g(\cdot, t)$, where $t \geq 0$, in the space of measurable bounded functions the dry-friction flow.

9. ASYMPTOTIC OPTIMALITY: PROOF

9.1. Asymptotic optimality of control: polar-like coordinate system. Here we present at an intuitive level reasons for asymptotic optimality of the control law (5). The rigorous treatment of asymptotic optimality is performed in the below. We define a polar-like coordinate system, well suited for representation of the

motion under the control u . Every state $0 \neq \mathbf{f}$ of the string can be represented uniquely as

$$(72) \quad \mathbf{f} = \rho\phi, \text{ where } \rho = \rho(x) \text{ is a positive factor, and } \phi \in \partial\Omega.$$

The pair ρ, ϕ is the coordinate representation for x , and $\rho(\phi) = 1$ is the equation of the “sphere” $\omega = \partial\Omega$. It is important that the set ω is invariant under free (uncontrolled) motion of our system (6). This follows from the similar invariance of the support function $H_\Omega(p)$ under evolution governed by $\dot{p} = -A^*p$. The latter invariance is clear, because the support function is an ergodic mean of the function $|\xi_1(0, t)|$ under the free motion. This implies invariance of the dual function $\rho = \rho(\mathbf{f})$, so that $\langle \partial\rho/\partial\mathbf{f}, A\mathbf{f} \rangle = 0$. Therefore, under the control u from (55) the total (Lie) derivative of ρ takes the following form:

$$(73) \quad \dot{\rho} = \left\langle \frac{\partial\rho}{\partial\mathbf{f}}, A\mathbf{f} + Bu \right\rangle = \left\langle \frac{\partial\rho}{\partial\mathbf{f}}, Bu \right\rangle = - \left| \left\langle \frac{\partial\rho}{\partial\mathbf{f}}, B \right\rangle \right|,$$

where the last identity holds because $\partial\rho/\partial\mathbf{f}$ is the outer normal to the set $\rho\Omega$. In particular, the “radius” ρ is a monotone non-increasing function of time. Moreover, the RHS of Eq. (73) necessarily equals -1 if $f_1(0) \neq 0$. For any other admissible control, we have

$$(74) \quad \dot{\rho} \geq - \left| \left\langle \frac{\partial\rho}{\partial\mathbf{f}}, B \right\rangle \right|.$$

The evolution of ϕ by virtue of system (6) is described by

$$(75) \quad \dot{\phi} = A\phi + \frac{1}{\rho}(Bu - \phi\dot{\rho}) = A\phi + \frac{1}{\rho} \left(Bu + \phi \left| \left\langle \frac{\partial\rho}{\partial\mathbf{f}}, B \right\rangle \right| \right).$$

We note that the right-hand side $- \left| \left\langle \frac{\partial\rho}{\partial\mathbf{f}}(\mathbf{f}), B \right\rangle \right|$ of Eq. (73) equals $- \left| \left\langle \frac{\partial\rho}{\partial\mathbf{f}}(\phi), B \right\rangle \right|$. Thus, the evolution of the RHS of Eq. (73) is determined by the evolution of ϕ by virtue of Eq. (75). It is clear that if ρ is large, then the second term in the RHS of (75) is $O(1/\rho)$ and affects the motion of ϕ over the “sphere” ω only slightly. Our next task is to compute approximately the “ergodic mean”

$$(76) \quad E_T = \frac{1}{T} \int_0^T \left| \left\langle \frac{\partial\rho}{\partial\mathbf{f}}, B \right\rangle \right| dt$$

of the RHS of Eq. (73) provided that ρ is large. Here B is a constant vector, while, according to the preceding arguments, the vector function

$$(77) \quad \frac{\partial\rho}{\partial\mathbf{f}}(t) := \frac{\partial\rho}{\partial\mathbf{f}}(\mathbf{f}(t))$$

behaves approximately as $e^{A^*t} \frac{\partial\rho}{\partial\mathbf{f}}(0)$. Therefore, the ergodic mean E_T is well approximated by

$$(78) \quad E_T = \frac{1}{T} \int_0^T \left| \left\langle e^{A^*t} \xi, B \right\rangle \right| dt,$$

where $\xi = \frac{\partial\rho}{\partial\mathbf{f}}(0)$. We know from Theorem 2 that as $T \rightarrow \infty$ the ergodic mean E_T tends to $H(\xi) = H(\frac{\partial\rho}{\partial\mathbf{f}})$. However, according to one of the basic “duality relation” (44), we know that $H(\frac{\partial\rho}{\partial\mathbf{f}}) = 1$.

Therefore, we conclude, by using abbreviation $\rho(t) = \rho(\frac{\partial\rho}{\partial\mathbf{f}}(\mathbf{f}(t)))$, that

$$(79) \quad (\rho(0) - \rho(T))/T = 1 + o(1), \text{ as } T \rightarrow \infty,$$

provided that we use the dry-friction control (55).

Under any other admissible control, according to Theorem 4,

$$(80) \quad (\rho(0) - \rho(T))/T \leq 1 + o(1).$$

These latter relations (79) and (80) express the asymptotic optimality we sought for.

9.2. Formal proof. Here we prove the asymptotic optimality of control (55) via the use of the function $g(x, t)$ from Eq. (57). The law of motion (61) is

$$(81) \quad g(z, t) = g(z + t, 0) - \sum_J \text{sign } g(0, z + t + 2k\pi),$$

where the set $J = J_t$ consists of $k \in \mathbb{Z}$ such that $z + 2k\pi \in [-t, 0]$. The functional ρ has the form $\rho(g) = 2\pi \sup_{x \in \mathbb{R}/2\pi\mathbb{Z}} |g(x, t)|$. The control $\text{sign } g(0, z + t)$ is not affected by the scaling transformation

$$(82) \quad g \mapsto \Phi = g/\rho.$$

However, if ρ is large, then our previous considerations reveal that the function $\Phi = g/\rho$ moves in an almost uncontrollable mode. The latter means that approximately

$$(83) \quad \Phi(x, t) \approx \Phi(x + t, 0),$$

so that we come to the approximate equality

$$\text{sign } g(0, z) \approx \text{sign } g(z, 0).$$

More precisely, suppose that in the time-interval $[0, T]$ we have $\rho(g_t) \geq 2\pi M$, where M is a (large) constant. In view of Eq. (67) we have

$$(84) \quad g(0, t) = g(t, 0) - \frac{1}{2} \text{sign } g(0, t) - \sum_{k \neq 0, 2k\pi \in [-t, 0]} \text{sign } g(0, t + 2k\pi),$$

and, therefore,

$$(85) \quad |g(0, t) - g(t, 0)| \leq \frac{t}{2\pi}.$$

Since $\rho(g) \geq M$ there exist points $x \in \mathbb{R}/2\pi\mathbb{Z}$, where either $g(x, 0) \geq M - 1$ or $g(x, 0) \leq -(M - 1)$. Assume for definiteness that $g(x, 0) \geq M - 1$. Then in view of Eq. (85), $\text{sign } g(0, t + 2k\pi) = +1$ for $t \in [0, T]$ provided that $\frac{T}{2\pi} \leq M - 1$. For instance, this is the case if M is large and $T = O(\sqrt{M})$.

In view of (81) this means that

$$(86) \quad g(z - t, t) = g(z, 0) - \frac{t}{2\pi} \text{sign } g(z, 0) + O(1),$$

where $|O(1)| \leq 1$, and $g(z, 0) \geq M - 1$. This implies that

$$(87) \quad \sup_z g(z, t) = \sup_z g(z, 0) - \frac{t}{2\pi} + O(1),$$

since $\text{sign } g(z, 0) = +1$ if $g(z, 0) \geq M - 1$. Since $\rho(t) = 2\pi \sup_z g(z, t)$ we obtain the approximate equality

$$(88) \quad (\rho(0) - \rho(t))/t = 1 + O(1/t),$$

provided that the length T of the time interval is less than $2\pi(M - 1)$.

By partition of any sufficiently long interval of time $[0, T]$ into many equal intervals of length $\leq 2\pi(M - 1)$ we come to the following precise result.

Theorem 6. *Consider evolution $\rho(t) = \rho(g_t)$ of ρ under control (81). Let*

$$(89) \quad M = \min\{\rho(0), \rho(T)\}.$$

Suppose that $M \rightarrow +\infty$, $T \rightarrow +\infty$. Then, we have

$$(90) \quad (\rho(0) - \rho(T))/T = 1 + O(1/T + 1/M).$$

Under any other admissible control,

$$(91) \quad (\rho(0) - \rho(T))/T \leq 1 + O(1/T + 1/M).$$

The preceding arguments of this Section prove statement (90) and statement (91) following from Theorem 4.

10. FEATURES OF THE DRY-FRICTION FLOW

Methods used in Section 8 allows revealing the basic properties of the dry-friction flow. In particular, it is possible to derive the asymptotic optimality of the dry-friction flow directly from Eqs. (68)–(70).

10.1. Far from the target. Indeed, it follows from equations (68), (69) that if $\sup_x g(x, 0) > 1/2$, then $\sup_{t \in [0, 2\pi]} \phi(t) = \sup_x g(x, 0) - 1/2$. The same estimates hold with essential supremum vraisup instead of the plain sup. In particular,

$$(92) \quad \|\phi_0\| = \|g\| - \frac{1}{2},$$

where ϕ_0 is the restriction of ϕ to the interval $[0, 2\pi]$, $g(x) = g(x, 0)$ is the initial data, and $\|f\|$ stands for the L_∞ -norm of f over the same interval $[0, 2\pi]$. From equation (70) it follows that

$$(93) \quad \|\phi_1\| = \|\phi_0\| - 1,$$

where ϕ_1 is the restriction of $\phi(t+2\pi)$ to the interval $[0, 2\pi]$. We denote by F_τ , where $\tau \geq 0$, shift of the argument $(F_\tau \phi)(t) := \phi(t + \tau)$. It is clear from the definition of the dry-friction flow Φ_τ and Eq. (92) that

$$(94) \quad \|F_\tau \phi\| = \|\Phi_\tau g\| - \frac{1}{2},$$

provided that $\|\Phi_\tau g\| \geq \frac{1}{2}$. Eq. (93) means that

$$(95) \quad \|F_{2\pi} \phi\| = \|\phi\| - 1.$$

These identities imply that for natural integers k

$$(96) \quad \|\Phi_{2k\pi} g\| = \|g\| - k,$$

provided that $\|g\| \geq k + \frac{1}{2}$. This can be restated in the notations of the preceding Section 9 as follows:

$$(97) \quad \frac{\rho(0) - \rho(2k\pi)}{2k\pi} = 1,$$

and gives a very precise form of the asymptotic optimality (see Theorem 6).

10.2. Near the target. On the contrary, if $\|g\| \leq \frac{1}{2}$, the dry-friction flow does not help to damp the string. Under this condition, we obtain from Eq. (68) and Eq. (69) that

$$(98) \quad \phi_0 = 0, \quad \text{sign } \phi_0 = -2g,$$

and from equation (70) we obtain that

$$(99) \quad \phi(t + 2\pi) = 0, \quad \text{sign } \phi(t + 2\pi) = 2g(t) = 2g(t, 0) = -\text{sign } \phi(t),$$

provided that $t \in [0, 2\pi)$. This means that the dry-friction flow is given by solution of the Cauchy problem for the linear equation

$$(100) \quad \left(\frac{\partial}{\partial t} - \frac{\partial}{\partial x} \right) g(x, t) = -2(-1)^k \delta(x) g(t, 0), \quad \text{if } t \in [2k\pi, 2(k+1)\pi).$$

The norm $\|\Phi_{2k\pi} g\| = \|\phi(t + 2k\pi)\|$ does not depend on the natural integer k .

It is easy to solve the Cauchy problem (100) explicitly. The solution $g(x, t)$ is determined via the initial data $G(x) = g(x, 0)$ as $g(x, t) = (-1)^k G(x + t)$ provided that $x \in [0, 2\pi)$ and $t \in [2k\pi, 2(k+1)\pi)$.

11. CONCLUSION

The subject of the present paper have arisen as a natural extension of our preceding study of finite systems of oscillators [2, 3]. There we put an emphasis on the case of non-resonant systems. Here we study the string which is an infinite system of highly resonant oscillators. In both cases the basic new results are the existence and uniqueness of the motion under the dry-friction control and the asymptotic optimality of the control.

The results of both studies are similar, but methods are rather different. The similarity of studies is especially far reaching in first parts of both of them, where we investigate the reachable sets and limiting capabilities of admissible controls. In some aspects the present case of a string is simpler than that of finitely many non-resonant oscillators. E.g., we do not use any special function, like the hypergeometric function in the sense of Gelfand or DiPerna–Lions theory [9], which play a decisive part in control of finite system of oscillators (see Refs. [3]). On the other hand the infinite dimensional case is related to well known and quite real analytic difficulties which are present (for details, see Appendix III).

Acknowledgements. This work was supported by the Russian Scientific Foundation, grant 16-11-10343.

APPENDIX I. SINGULAR ARCS I

The above analysis of the dry-friction control near the target extends to more general analysis of the motion along singular arcs. These are by definition the time-intervals, where in the controlled motion

$$(A1) \quad \left(\frac{\partial}{\partial t} - \frac{\partial}{\partial x} \right) g(x, t) = \delta(x)u(t), \quad u = -\text{sign } g(0, t)$$

the control is not uniquely defined by the current state of the string, i.e. $g(0, t) \equiv 0$.

In order to construct a motion of this kind we use the spectral decompositions $g(x, t) = \sum g_\mu(x)e^{i\mu t}$, and $u(t) = \sum u_\mu e^{i\mu t}$. This almost periodic function should be bounded: $|u| \leq 1$. Then, the functions g_μ should satisfy

$$(A2) \quad i\mu g_\mu - \frac{\partial}{\partial x} g_\mu = -\delta u_\mu, \quad \text{and } g_\mu(0) = 0.$$

The first equation (A2) guarantees that 0 is the point of discontinuity of g_μ , so that the second equation (A2) should be treated cautiously. In fact, the discussion of Section 8 shows that we have to take $\frac{1}{2}(g_\mu(0+) + g_\mu(0-))$ for $g_\mu(0)$. Indeed, according to the first equation (A2), the function g_μ is piecewise differentiable with jumps at $x = 0$. Therefore 2π -periodic function g_μ should have the form

$$(A3) \quad g_\mu(x) = C_\mu e^{i\mu x} \text{ for } x \in [0, 2\pi),$$

where the constant $C_\mu = (1 - e^{2\pi i\mu})^{-1}u_\mu$. The condition $g_\mu(0) = 0$ gives

$$(A4) \quad 1 + e^{2\pi i\mu} = 0,$$

which implies that μ should have the form $\mu = \frac{1}{2}\nu$, where ν is an odd integer, and $C_\mu = u_\mu/2$. Therefore, the control $u(t) = \sum u_\mu e^{i\mu t}$ is not just almost periodic but 4π -periodic. Moreover, we have

$$(A5) \quad g(x, t) = \sum g_\mu(x)e^{i\mu t} = \frac{1}{2} \sum u_\mu e^{i\mu(t+x)} = \frac{1}{2}u(t+x) \text{ for } x \in [0, 2\pi).$$

APPENDIX II. SINGULAR ARCS II

It is possible in a more general fashion analyze the singular arcs of the motion governed by the second-order nonlinear wave equation (56). We will do this by the direct finite-dimensional approximation of the string by finite number of harmonics. These arcs are the time-intervals of the motion, where the semi-flow $\mathbf{f} \rightarrow \phi_t(\mathbf{f}) = \mathbf{f}_t$ leaves invariant the “hyperplane” $f_1(0) = 0$, where the control $u = -\text{sign}(f_1(0))$ is not uniquely defined. We put the word hyperplane into quotation marks because the value $f_1(0)$ is badly defined within the natural state space of the string. In order to be correct, we introduce a cut-off. Namely, we start with an approximation of the string with first N harmonics:

$$(A6) \quad \begin{aligned} f_0(x) &= \sum_{k=0}^N a_k \cos kx \text{ modulo constants } a_0, \\ f_1(x) &= \sum_{k=0}^N b_k \cos kx, \end{aligned}$$

and consider in this $2N + 1$ -dimensional space the correctly defined ODE

$$(A7) \quad \begin{aligned} \dot{a}_0 &= b_0 & \dot{a}_k &= b_k \\ \dot{b}_0 &= u, & \dot{b}_k &= -k^2 a_k + 2u, \quad k = 1, \dots, N, \end{aligned}$$

which is the natural finite-dimensional approximation of the wave equation.

We require that $\sum_{k=0}^N b_k = 0$ which is a restatement of the condition $f_1(0) = 0$. This immediately implies that $u = \frac{1}{2N+1} \sum_{k=0}^N k^2 a_k$. Thus, we obtain a linear differential equation

$$(A8) \quad \begin{aligned} \dot{a}_k &= b_k \\ \dot{b}_k &= -k^2 a_k + \frac{1}{2N+1} \sum_{k=1}^N k^2 a_k, \quad k = 1, \dots, N. \end{aligned}$$

in the space $\mathbb{R}^{2N}$ of sequences $a_k, b_k, k = 1, \dots, N$. We are going to solve system (A8) and then remove the cut-off: In other words, we pass to the limit $N \rightarrow \infty$ in the obtained solution. To obtain the solution we first find the “spectral decomposition” of the linear operator given by the RHS of Eq. (A8). The corresponding eigenvalue problem is:

$$(A9) \quad \begin{aligned} \lambda a_l &= b_l \\ \lambda b_l &= -l^2 a_l + \frac{2}{2N+1} \sum_{k=1}^N k^2 a_k, \quad l = 1, \dots, N, \end{aligned}$$

which is equivalent to

$$(A10) \quad (l^2 + \lambda^2) a_l = \frac{2}{2N+1} \sum_{k=1}^N k^2 a_k, \quad l = 1, \dots, N.$$

This, in turn, is equivalent to the system

$$(A11) \quad \begin{aligned} a_k &= \frac{R}{k^2 + \lambda^2}, \\ \frac{2}{2N+1} \sum_{k=1}^N \frac{k^2}{k^2 + \lambda^2} &= 1. \end{aligned}$$

Here $R = R_\lambda$ is an arbitrary k -independent constant. Thus, the eigenvalue problem reduces to the solution of

$$(A12) \quad \frac{2}{2N+1} \sum_{k=1}^N \frac{k^2}{k^2 + \lambda^2} = 1.$$

It is easy to show that the problem (A12) has $2N$ purely imaginary eigenvalues $\lambda = i\mu$. Indeed, this statement is equivalent to the fact that the polynomial equation of

degree N

$$(A13) \quad \frac{2}{2N+1} \sum_{k=1}^N \frac{k^2}{k^2 - t} = 1.$$

has N real roots. It is clear, at least when N is large, that there is a positive root t in a close vicinity of zero, and that the function $t \mapsto \sum_{k=1}^N \frac{k^2}{k^2 - t}$ tends to $+\infty$ as $t \rightarrow k^2 - 0$, and tends $-\infty$ as $t \rightarrow k^2 + 0$ for $k = 1, \dots, N$. This implies that each interval $[k, k+1]$ for $k = 0, \dots, N-1$ contains a root t_k .

Now we pass to the limit $N \rightarrow \infty$ in Eq. (A12) and Eq. (A13). To do this we rewrite Eq. (A12) in the following form:

$$(A14) \quad \sum_{k=1}^N \frac{k^2 - \mu^2}{k^2 - \mu^2} + \mu^2 \sum_{k=1}^N \frac{1}{k^2 - \mu^2} = N + \frac{1}{2},$$

which is equivalent to

$$(A15) \quad \sum_{k=1}^N \frac{1}{k^2 - \mu^2} = \frac{1}{2\mu^2}.$$

The function $g_N(\mu) = \sum_{k=1}^N \frac{1}{k^2 - \mu^2}$ has then a well-defined limit as $N \rightarrow \infty$. Namely,

$$(A16) \quad \lim_{N \rightarrow \infty} g_N(\mu) = \sum_{k=1}^{\infty} \frac{1}{k^2 - \mu^2} - \frac{1}{2\mu^2} = \frac{\pi}{2\mu} \operatorname{ctg}(\pi\mu) = g(\mu),$$

and the limit eigenvalues $i\mu$ are given by roots $\mu_k = k + \frac{1}{2}$ of $\operatorname{ctg}(\pi\mu)$. Here μ_k is the unique solution of $\operatorname{ctg}(\pi\mu)$ in the interval $[k, k+1]$. The spectral decomposition is defined by the correspondence

$$(A17) \quad a_k = \sum_{\mu} \frac{R_{\mu}}{k^2 - \mu^2}$$

between infinite sequences a_k and R_{μ} .

Remark. We have the following result:

Theorem A1. (cf. the “Eisenstein”-part of Ref. [8])

$$(A18) \quad \sum_{k=1}^{\infty} \frac{1}{k^2 - \mu^2} \cos kx - \frac{1}{2\mu^2} = -\frac{1}{|\mu|} \sin \|\mu x\|_{\mu}, \quad \text{where } \|y\|_{\mu} = \inf_{n \in \mathbb{Z}} |y + 2\pi\mu n|$$

Proof. Indeed, operator $L = \frac{\partial^2}{\partial x^2} + \mu^2$, when applied to LHS and RHS of (A18) gives $-\delta(x)$, and the kernel of L in the space of 2π -periodic functions is 0. $\square$

This fact allows to rewrite the transform (A17) in its functional form as follows:

$$(A19) \quad \begin{aligned} f_0(x) &= \sum a_k \cos kx = -\sum_{\mu} \frac{\Re R_{\mu}}{|\mu|} \sin \|\mu x\|_{\mu} \\ f_1(x) &= \sum b_k \cos kx = -\sum_{\mu} (\operatorname{sign} \mu) \Im R_{\mu} \sin \|\mu x\|_{\mu} \end{aligned}$$

The sequence of complex numbers R_{μ} is self-adjoint, meaning that $R_{-\mu} = \overline{R_{\mu}}$. Thus, the solution of Eq. (50) along a singular arc has the form $f(x, t) = \sum a_k(t) \cos kx$, where

$$(A20) \quad a_k(t) = \sum_{\mu} \frac{R_{\mu} e^{i\mu t}}{k^2 - \mu^2} = 2 \sum_{\mu > 0} \frac{\Re(R_{\mu} e^{i\mu t})}{k^2 - \mu^2},$$

and μ runs over roots $\mu_k = k + \frac{1}{2}$ of the function $\operatorname{tg}(\pi\mu)$.

The point with coordinates a_k, b_k belongs to the singular arc at the cut-off level N if the control $u = \frac{1}{N+1} \sum_{k=0}^N k^2 a_k$ satisfies the bound $|u| \leq 1$. The problem is to pass to the limit $N \rightarrow \infty$ in this condition. In terms of the variables R_μ the condition tells that

$$(A21) \quad \left| \frac{1}{N+1} \sum_{k \in [1, N], \mu \in (0, N)} \frac{k^2 \Re(R_\mu)}{k^2 - \mu^2} \right| \leq \frac{1}{2}.$$

The sum

$$(A22) \quad \frac{1}{N+1} \sum_{k=1}^{k=N} \frac{k^2}{k^2 - \mu^2} = \frac{1}{N+1} (N + \mu^2 g_N(\mu)) = \frac{1}{N+1} (N+1 + \mu^2 g_N(\mu) - 1)$$

equals to 1 because of equation (A15): $\mu^2 g_N(\mu) = 1$. Therefore, the condition (A21) at the cut-off level N can be restated as follows:

$$(A23) \quad \left| \sum_{\mu \in (0, N)} \Re(R_\mu) \right| \leq \frac{1}{2}.$$

The formal passage to the limit $N \rightarrow \infty$ transforms (A23) into

$$(A24) \quad \left| \sum_{\mu > 0} \Re(R_\mu) \right| \leq \frac{1}{2}.$$

We note that the summation in Eq. (A23) and Eq. (A24) goes over different sets of roots μ : in the first case over roots of $\mu^2 g_N(\mu) = 1$, and in the second case over roots of $\mu^2 g(\mu) = 1$.

The time-limits of the arc are determined by the inequality

$$(A25) \quad \left| \sum_{\mu > 0} \Re(R_\mu e^{i\mu t}) \right| \leq \frac{1}{2},$$

which says that the control u satisfies $|u| \leq 1$. Eq. (A21) and Eq. (A20) together determine at a formal level the singular motion of the system. In order to make these considerations applicable to the “real” string, we need to know the continuity properties of the function

$$(A26) \quad t \mapsto \sum_{\mu > 0} \Re(R_\mu e^{i\mu t}),$$

when the function $\frac{\partial f_0}{\partial x} + f_1$ is bounded, and related to the sequence R_μ via Eq. (A20).

APPENDIX III. CONTRACTING PROPERTIES OF THE DRY-FRICTION CONTROL

We consider the semi-flow $\mathbf{f} \rightarrow \phi_t(\mathbf{f}) = \mathbf{f}_t$, defined by Cauchy problem for the nonlinear string equation (6) of second order. Here we will show that at formal level the semi-flow $\mathbf{f} \rightarrow \phi_t(\mathbf{f}) = \mathbf{f}_t$ is continuous, and even contracting wrt the “spacial” argument $\mathbf{f}$. Indeed, consider the functional of energy

$$(A27) \quad E(\mathbf{f}) = \frac{1}{2} \|\mathbf{f}_1\|^2 + \frac{1}{2} \left\| \frac{\partial f_0}{\partial x} \right\|^2,$$

where $\|\cdot\|$ is the $L_2(0, 2\pi)$ -norm. We have the following basic a priori estimate

$$(A28) \quad \frac{d}{dt} E(\phi_t(\mathbf{f}) - \phi_t(\mathbf{g})) \leq 0.$$

Indeed, by formal computation we have for $E(t) = E(\phi_t(\mathbf{f}) - \phi_t(\mathbf{g}))$ that

$$\begin{aligned} \frac{d}{dt}E &= A + B + C, \text{ where} \\ (A29) \quad A &= \left\langle \frac{\partial}{\partial x}(f_{t0} - g_{t0}), \frac{\partial}{\partial x}(f_{t1} - g_{t1}) \right\rangle, \\ B &= \langle f_{t1} - g_{t1}, \Delta(f_{t0} - g_{t0}) \rangle, \\ C &= -(f_{t1}(0) - g_{t1}(0))(\text{sign } f_{t1}(0) - \text{sign } g_{t1}(0)). \end{aligned}$$

We have $A + B = 0$, because $\langle v, \Delta u \rangle = -\langle \frac{\partial v}{\partial x}, \frac{\partial u}{\partial x} \rangle$ for any pair u, v of periodic functions. Therefore,

$$(A30) \quad \dot{E} = A + B + C = C.$$

Denote $x = f_{t1}(0)$, $y = g_{t1}(0)$. We have $C = -(x - y)(\text{sign } x - \text{sign } y) \leq 0$, because the sign-function is monotone. This implies inequality (A28) which, in turn, implies that the map $\mathbf{f} \mapsto \phi_t(\mathbf{f})$ is contracting wrt the energy-norm for $t \geq 0$. These considerations are formal, because are based on the formal differentiation of a product of distributions.

This becomes even more clear if we rewrite the above formal computation in the simpler case of the nonlinear string equation (58) of the first order. In this case the energy is

$$(A31) \quad E(g) = \frac{1}{2} \|g\|^2 = \frac{1}{2} \int g(x)^2 dx,$$

where integration is over the torus $\mathbb{R}/2\pi\mathbb{Z}$. Formally, if $E(t) := E(\Phi_t(g) - \Phi_t(f))$, then

$$\begin{aligned} \frac{d}{dt}E &= A + B, \text{ where} \\ (A32) \quad A &= \left\langle \frac{\partial}{\partial x}(f - g), (f - g) \right\rangle, \\ B &= -(f(0) - g(0))(\text{sign } f(0) - \text{sign } g(0)). \end{aligned}$$

The term $A = 0$ for any pair of periodic functions f, g , and the term B is non-positive since the sign-function is monotone. Thus, the dry-friction semi-flow Φ_t is contracting wrt the energy-norm.

It is not clear to us whether the dry-friction flow rigorously constructed in Section 8 is contracting indeed wrt the energy norm.

REFERENCES

- [1] E.V. GONCHAROVA AND A.I. OVSEEVICH. *Comparative analysis of the asymptotic dynamics of reachable sets to linear systems*, Journal of Computer and Systems Sciences International, **46** (2007), 4, 505–513.
- [2] A.I. OVSEEVICH AND A.K. FEDOROV. *Asymptotically optimal feedback control for a system of linear oscillators*, Doklady Mathematics, **88** (2013), 2, 613–617.
- [3] A.K. FEDOROV AND A.I. OVSEEVICH. *Asymptotic control theory for a system of linear oscillators*, Moscow Mathematical Journal, **16** (2016), 3, 561–598.
- [4] A.I. OVSEEVICH AND A.K. FEDOROV. *Asymptotically optimal control for a simplest distributed system*, arXiv:1612.01485.
- [5] J.L. LIONS. *Exact controllability, stabilization and perturbations for distributed systems*, SIAM Review, **30** (1988), 1, 1–68.
- [6] A.F. FILIPPOV. *Differential equations with discontinuous righthand sides*. Springer, 1988.
- [7] I.A. BOGAEVSKII. *Discontinuous gradient differential equations and trajectories in calculus of variations*, Sbornik: Mathematics, **97** (2006), 12, 1723–1751.
- [8] A. Weil. *Elliptic Functions according to Eisenstein and Kronecker*, Springer Verlag, Ergebnisse der Mathematik und ihrer Grenzgebiete, Vol. 88 (1976).
- [9] R.J. DiPERNA AND P.L. LIONS. *Ordinary differential equations, transport theory and Sobolev spaces*, Inventiones mathematicae, **98** (1989), 511–547.

LPTMS, CNRS, UNIV. PARIS-SUD, UNIVERSITÉ PARIS-SACLAY, 91405, 100 BÂTIMENT, 15 RUE
GEORGES CLÉMENCEAU, ORSAY, FRANCE, ALEKSEY.FEDOROV@LPTMS.U-PSUD.FR

INSTITUTE FOR PROBLEMS IN MECHANICS, RUSSIAN ACADEMY OF SCIENCES, 119526, VERNAD-
SKY AV., 101/1, MOSCOW, RUSSIA, OVSEEV@IPMNET.RU